

XDS-1100

Universal and scalable collaboration solution for any 3D display



The XDS-1100 multi-channel video processor solution is designed specifically to enable collaboration on large multi-channel displays, making full use of the increased resolution and availability of 3D stereo content.

The XDS-1100 series enables you to display up to twelve hardwired mono and 3D stereo sources simultaneously on any type of multi-channel display canvas. The XDS-1100 allows displaying a PC cluster with any of the sources connected to the unit in an easy way. The integrated user-friendly desktop, Barco's XDS Control Center software running on a supported Windows Operating System, allows you to enjoy mouse and keyboard control of the sources you need in a familiar Windows desktop environment. With the optional XDS User Client software, additional computers can be displayed through the network.

Available for any display system

Barco's XDS display management system works with regular or active 3D stereo projectors, modular rear-projected cube walls, or near-seamless flat panel walls, so that you can enjoy the collaborative advantages of XDS Control Center software in any type of room. With up to 18 inputs and the possibility to drive up to 8 output channels, depending on the configuration, the XDS-1100 is an indispensable tool in demanding work environments such as automotive and product design, geophysical data analysis or architectural simulation.

Wide connectivity, easy collaboration

By seeing several sources at the same time, you can quickly discover correlations between data, or process various types of information faster. But Barco's XDS concept allows more. It enables you to connect to and control remote computers on the display, features easy-to-use videoconferencing control, and allows other users to create and store predefined screen layouts. The XDS-1100 is designed to make collaborative team work with 3D stereo easier, faster and more efficient.

BARCO

Visibly yours

Technical specifications

Output channels	Up to 8 (higher number of outputs available as non-standard functionality)
PiP inputs	up to 18
Desktop inputs	As many as there are output channels slots pre-equipped Each desktop input signal must have the same resolution as the output channel
Cluster PC input	As many as there are output channels slots pre-equipped Each cluster input signal must have the same resolution as the output channel (in this case the number of PiP inputs is limited to 11)
Stereo support	Any PiP input can be an active stereo signal, including the Cluster PC input All outputs can be set to active stereo, left mono or right mono
I/O properties	All interfaces are dual link DVI-I Analog I/O: 50-270 MHz pixel clock Digital I/O: 50-280 MHz pixel clock All interfaces have a Mini Din 3 stereo sync connector
I/O resolution limits	UXGA (1600x1200) active stereo at 120 Hz HDTV (1920x1080) active stereo at 110 Hz WUXGA (1920x1200) active stereo at 100 Hz WQXGA (2560x1200) active stereo at 60 Hz
Overlap support	Up to 100% horizontal and vertical Overlap possible
Software	XDS Control Center software v3 or higher needed
Power	110-220 V 800 W max
Dimensions	19" rack mountable 9U high Keep 1U free space under and above unit for cabling